1

GEM1006

AN EMULATION METHOD FOR MANAGING A READER FOR A CHIP
CARD INCOMPATIBLE WITH AN ENVIRONMENT

The invention concerns chip card readers
5 functioning according to the "EMV" standard and able to
be used in a PCSC-standard environment and, more
particularly, a method of emulating the PCSC
environment in order to manage the EMV-standard reader.

The acronym "EMV" refers to a standard known by
10 the English expression "Europay Mastercard and Visa"
and the acronym "PCSC" refers to a standard known by
the English expression "Personal Computer Smart Card".

Microcircuit cards or chip cards are for example
used for making transactions, notably monetary
15 transactions, and function in accordance with strict
rules with a view to guaranteeing the security of the
transactions. These rules are complied with when the
chip card and reader function according to the "EMV"
standard.

2

However, the chip card reader to the EMV standard can be caused to be used in association with a personal computer connected, for example, to a network of the Internet type in order to perform electronic
5   transactions.   This   association   presents incompatibilities with regard to the communication of the chip card.

There is therefore a need to mitigate these incompatibilities so as to be able to use a chip card
10   reader to the EMV standard in association with a personal computer which can communicate with a chip card according to the PCSC standard.

To this end, the invention provides that the personal computer emulates the functionalities of a
15   PCSC standard reader with regard to communication with the chip card reader, which allows communication between the reader and personal computer.

The invention therefore concerns a method of emulating a chip card reader functioning according to
20   the PCSC standard in order to manage a chip card reader functioning according to the EMV standard and communicating with the chip card according to the protocol T = 0, characterised in that it comprises the following operations consisting of:
25   (a) determining the type of APDU exchanges for which it is necessary to effect an emulation,

(b) emulating the return of a state word (SW1, SW2) in compliance with the standards to the PCSC environment,

3

(c) when the type of APDU exchange corresponds to a Case 2 as defined in ISO 7816-4, receiving the command C-APDU complying with the state word,

(d) when the type of APDU exchange corresponds to
5   a Case 4 as defined in the standards, receiving the command GET-RESPONSE using the state word,

(e) returning R-APDU in response to C-APDU or to GET-RESPONSE.

According to the invention, operations (c) and
10   (d) can be performed in the reverse order.

Operation (c) can be followed by the following operation consisting of:

(c_1) emulating the return of a state word (SW1, SW2) complying with the standards to the PCSC
15   environment as provided for when the type of APDU exchange corresponds to a Case 4.

Operation (b) can be replaced by operations (b' and b") and operation (d) replaced by an operation (d") consisting of:

20   (b') emulating an alarm state, which can relate to the application of the chip card, sending to the PCSC environment the state word (SW1, SW2) complying with the standards,

(d') receiving   the   command   GET-RESPONSE
25   parameterised such that the number of bytes awaited is 0,

(b") emulating a state word (SW1, SW2), complying with the standards, to the PCSC environment as provided for when the type of APDU exchange corresponds to Case
30   4.

4

Other characteristics and advantages of the
present invention will emerge from the reading of the
following description of a particular example
embodiment, the said description being given in
5 relation to the accompanying drawing, in which:
        - the single figure is a flow diagram
illustrating the method according to the invention.

The personal computer with which the chip card
reader to the EMV standard must communicate comprises a
10 communication interface, referred to as "IFD Handler",
"IFD" being the acronym for the English expression
"Interface Divide".

According to the invention, this interface is
used for emulating the functionalities of a reader to
15 the PCSC standard. This interface receives from the
application a command C-APDU which transmits it to the
reader, which in return sends a response R-APDU. APDU
is the acronym of the English expression "Application
Protocol Data Unit". Knowing C-APDU, R-APDU and the
20 fact that the protocol is of the type $T = 0$, the IFD
interface is in a position to determine whether it is
appropriate to make an emulation according to the
circumstances which it can detect.

This emulation must be effected for the APDU
25 exchange of Case 2 or Case 4 of ISO 7816-4 inspiring
the PCSC standard, and this for a communication
according to the protocol $T = 0$.

The starting state is defined by state 10 of the
flow diagram in the single figure. Step 12 consists of
30 detecting whether it is a question of a Case 2, this

5

case being characterised by the content of C-APDU, that
is to say containing a parameter Le indicating the
number of bytes of the data of R-APDU and not
containing any input date. In this case, the interface
5   must emulate the return of a state word consisting of
two bytes of value SW1=6C and SW2=Lx, Lx being the
number of bytes of the data of R-APDU. In return, it
receives a repetition of C-APDU with Le=Lx.

      In response to this new command, it is possible
10 to return the R=APDU with the same number Lx of bytes.
If Case 2 is not detected by step 12, step 14 makes it
possible to detect a Case 4 which is characterised by
the parameter Le in the presence of input data in C-
APDU. In this case, the interface must emulate the
15 return of a state word consisting of two bytes of value
SW1=61 and SW2=Lx. In return, it receives a command
called "GET-RESPONSE", which comprises a parameter
Le=Lx. In response to this command, the interface
sends back the R-APDU previously received from the
20 reader.

      If neither of these two types of APDU exchange,
Case 2 or Case 4, is detected, it is not necessary to
effect an emulation and R-APDU is returned without
emulation.

25   It should be noted that Case 2 can be dealt with
by passing through the Case 2 emulation phase with any
Lx, and then the Case 4 emulation phase with the
appropriate value Lx. After step 16, step 18 is passed
through, as indicated in dotted lines 30 in the single
30 figure, before going to step 20.

6

With regard to Case 4, an alarm state 24 can be emulated by passing through 26, as provided for by ISO 7816 or EMV in which

SW1 = 62 or 63, and

5   SW2 = xx or xx

or something connected with the application in the card with

SW1 = 9x and SW2 = xx

SW1 ≠ 90 and SW2 ≠ 00.

10

In return, it receives the command GET-RESPONSE parameterised so that the number of bytes expected is 0.

The emulation ends with step 16, and then step 20
15   via the connection 28.

The description which has just been given shows the steps of an emulation method which comprises the following operations consisting of:

(a) determining the types of APDU exchanges for
20   which it is necessary to effect an emulation,

(b) emulating the return of a state word (SW1, SW2) in compliance with the standards to the PCSC environment,

(c) when the type of APDU exchange corresponds to
25   a Case 2 as defined in ISO 7816-4, receiving the command C-APDU complying with the state word,

(d) when the type of APDU exchange corresponds to a Case 4 as defined in the standards, receiving the command GET-RESPONSE using the state word,

7

   (e) returning R-APDU in response to C-APDU or to GET-RESPONSE.

   In this method, operations (c) and (d) can be in the reverse order.

5   Operation (c) can be followed by the following operation consisting of:

   (c_1) emulating the return of a state word (SW1, SW2), complying with the standards, to the PCSC environment as provided for when the type of APDU

10 exchange corresponds to a Case 4.

   Operation (b) can be replaced by operations (b' and b") and operation (d) replaced by the operation (d') consisting of:

   (b') emulating an alarm state, which can relate to

15 the application of the chip card, sending to the PCSC environment the state word (SW1, SW2) complying with the standards,

   (d') receiving the command GET-RESPONSE parameterised and such that the number of bytes awaited

20 is 0,

   (b") emulating a state word, (SW1, SW2), complying with the standards, to the PCSC environment as provided for when the type of APDU exchange corresponds to Case 4.